

## Confidea DIV/CIV

WIRELESS VOTING UNIT WITH CHANNEL SELECTOR

Art. 71.98.0004 / 71.98.0014



Confidea DIV



Confidea CIV

### Description

The Confidea wireless unit combines a slim, contemporary design, excellent intelligibility and ease of use with a robust and reliable wireless connection which sets it apart from traditional wireless systems.

It allows a delegate/chairman of a conference to speak, request-to-speak and listen to the speaker or their preferred available language.

The units are equipped with a microphone On/Off or request-to-speak button, a single channel selector and five voting buttons.



The chairman unit comes with an additional priority, next-in-line and system volume adjustment button.

The Confidea units have the capability of receiving up to 16 translation channels. Up to 8 microphones can be open at the same time.

Using the Televic software suite voting sessions can be initiated. Features like voting agenda, voting setup and result logging are included. Results of a voting session can be displayed on screens using the visualisation module of the software suite.

Battery management is crucial using a wireless conference system. Therefore Confidea units combine a smart power management with an easy to replace removeable Lithium-ion battery pack. This results in a controllable and flexible recharging schedule. (Confidea BP, to be ordered separately)

A screw lock connector is provided to connect a removable microphone which is immune against GSM disturbances (MIC 38SL, to be ordered separately).

To prevent eavesdropping and unauthorized access, the Confidea® wireless system and the discussion units have a digital encryption mechanism to keep information of the meeting confidential.

---

## Controls and Features

- Built-in high quality loudspeaker which is automatically muted when the microphone is active, to prevent acoustic feedback.
- Microphone On/Off or request-to-speak button with two signalling LEDs
- Two headphone outputs
- One headphone volume adjustment
- Channel Up/Down adjustment
- OLED channel and volume information display
- Five voting buttons
- The chairman version (CIV) comes with a priority, next-in-line and system volume adjustment button

## Specifications

Technical Data	
Audio quality	16 bit digital
Headphone load impedance	> 32 ohm < 1k ohm
Output power	16.5 mW / 32 ohm
Power Supply	Battery pack
Dimensions	230(w), 130(h), 60(d)
Weight (g)	460
Color	RAL9011
Part number	Confidea DIV 71.98.0004 Confidea CIV 71.98.0014

## Status Control

- Red battery status LED  
4 h remaining : 1 Hz blinking  
2h remaining : 2 Hz blinking  
1h remaining : 4 Hz blinking
- Blue link status LED  
Off : connection established  
Blinking : low link quality
- Blue link status LED + Microphone LED  
Blinking : out of range, shutdown after 2 min.

## Accessories

- Removeable microphone  
MIC38SL 71.98.0050
- Battery pack  
Confidea BP 71.98.0042
- Transport case  
Confidea CHC 71.98.0044
- Headphones  
TEL151 71.04.0151

## Connectivity

- Two 3.5 mm jack plugs for headphones
- Battery pack connection
- Screw lock socket to connect removable microphone